

PARIS CHARLES DE GAULLE (LFPG)

Réacteurs (R) et hélices (H) / Jets (R) and propellers (H)

RWY 08L - 08R

Protégés pour / Protected for CAT A, B, C, D

| SID RNAV POGO RWY 08L-08R |                      |                         |          |                   |                    |               |                |                              |                              |          |
|---------------------------|----------------------|-------------------------|----------|-------------------|--------------------|---------------|----------------|------------------------------|------------------------------|----------|
| RMK                       | GNSS ou / or DME/DME |                         |          | MAG VAR 2020      |                    |               | 1.1°E          |                              | Ref NAVAID : PGS             |          |
| Procedure Identification  | Path Terminator      | Waypoint Identification | Fly Over | Direction MAG (°) | Direction True (°) | Distance (NM) | Turn direction | MNM Altitude (FL or AMSL ft) | MAX Altitude (FL or AMSL ft) | Nav Spec |
| PO 6H                     |                      |                         |          |                   |                    |               |                |                              |                              |          |
| RWY08L                    | CF                   | PG081                   | -        | 084               | 085.4              | -             | -              | -                            | -                            | RNAV 1   |
| RWY08R                    |                      |                         | -        | 081               | 082.4              | -             | -              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG084                   | Yes      | 084               | 085.5              | 4.8           | -              | 2000                         | 2000                         | RNAV 1   |
| -                         | DF                   | PG109                   | -        | -                 | -                  | -             | R              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG800                   | -        | 229               | 230.2              | 24.0          | -              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG801                   | -        | 271               | 272.4              | 4.1           | -              | -                            | -                            | RNAV 1   |
| -                         | FM                   | PG801                   | -        | 271               | 272.4              | -             | -              | -                            | -                            | -        |
| PO 6L                     |                      |                         |          |                   |                    |               |                |                              |                              |          |
| RWY08L                    | CF                   | PG081                   | -        | 084               | 085.4              | -             | -              | -                            | -                            | RNAV 1   |
| RWY08R                    |                      |                         | -        | 081               | 082.4              | -             | -              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG082                   | Yes      | 084               | 085.5              | 2.7           | -              | -                            | -                            | RNAV 1   |
| -                         | DF                   | PG085                   | -        | -                 | -                  | -             | -              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG802                   | -        | 187               | 187.7              | 9.2           | R              | -                            | -                            | RNAV 1   |
| -                         | TF                   | PG803                   | -        | 254               | 254.9              | 5.0           | -              | -                            | 4000                         | RNAV 1   |
| -                         | FM                   | PG803                   | -        | 254               | 254.9              | -             | -              | -                            | -                            | -        |